

Why does my Assembly say <Level of Detail1>?

LOD states are created automatically when you suppress components while in the master LOD. To save suppressions to a new LOD representation, click Save and you will be prompted to click Yes or No to save the LOD. If you choose yes, you can specify a name for the LOD. If you choose No, the suppression states of the component are discarded and the assembly is saved in master LOD.

Temporary LOD representations are created in subassemblies when a subassembly component is suppressed from a top level assembly. A tilde and index number are listed after the subassembly name to denote a temporary Level of Detail state. Note that the subassembly is not modified. You can open the subassembly on its own and save the suppression states as a named LOD if desired.